

Integra series

SAF Tehnika – the pioneer of compact full outdoor microwave radio technology – is excited to take a step forward in the evolution of full outdoor packet microwave radio systems. Integra is an unbelievably light, energy efficient, carrier-grade system that exemplifies an outstanding return on smart engineering - the synergy of high competence in radio electronics and materials science. Integration of the next generation microwave radio with high and super high-performance antennas into a single unit translates into a lower total cost of ownership, as well as less time spent on the installation site, and better reliability of the link even in densely served areas.

Perfect for small-cell, RAN, and HetNet backhaul where aesthetics in a metropolitan area is key concern, Integra delivers ambitious performance in a compact package never before available in licensed microwave backhaul. Integra's embedded software takes full advantage of its cutting-edge network processor providing SyncE support for LTE network, builds Layer 2 header compression and 256-bit AES encryption for public safety, government, and enterprise networks. Thanks to a convenient design and its solid functionality Integra is an industry-unique microwave system with a superior radiation pattern and payload capacity of up to 1 Gbps.

Integra – by its form and specification – is a proper building block for a variety of modern wireless networking applications. To stay advanced and competitive in the telecom world increasingly depends on seamless integration and interoperability of synchronization-sensitive systems. It is smart to invest in technology that takes the right direction: the concept of Integra is on that path.



SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia

Technical specification

	Integra-G	Integra-W
General		
Concept / form factor	FODU (Full-outdoor unit), directly mounted to the antenna	
Frequency bands	5.8 GHz UL, 6GHz, 7GHz, 8GHz, 11GHz, 13GHz, 15GHz, 17GHz UL, 18GHz, 23GHz, 24GHz UL, 25GHz, 26GHz, 28GHz, 38GHz, and more*	
Radio standards	EN 302 217-2 v3.1.1, EN 300 t+40-2 v1.4.1, FCC CFR 47 Part 101, Industry Canada RSS-GEN and relevant SRSP Specifications	
Frequency stability	± 10 ppm	
Capacity	Up to 1Gbps* with HC at 1+0 or 2+0	883 Mbps at 112 MHz 1024QAM 643 Mbps at 80 MHz 1024QAM (for Integra-W 17GHz and 24GHz)
	491 Mbps at 60 MHz 2048QAM	
Max modulation	2048QAM	1024QAM
Configurations	1+0, 2+0 link bonding, 1+1 HSB	1+0
ACM and ATPC	Yes	Yes
Channel bandwidth	ETSI: from 1.75* MHz, up to 56 MHz FCC: from 5 MHz, up to 60 MHz	ETSI: from 56 MHz, up to 112 MHz FCC: from 40 MHz, up to 80 MHz
Ports		
Gigabit Ethernet	1x RJ-45	Electrical with built-in PoE splitter and surge arrestor
	2x SFP	Fiber Optics
Service ports	3.5mm	Audible alignment and RSSI
	USB B	RS232 serial over USB B-Type
	LED	Power On, Link Synchronization, RSL, Polarization accuracy*
Ethernet		
Ethernet	GbE Network Processor built-in	Unmanaged Gigabit Ethernet
MAC Table size	32K entries	-
VLAN	802.1Q 4096 VLANs, QinQ	Transparent
Quality of Service	8 level 802.1p, 64 level DSCH, CoS, MPLS-TP exp bit	Transparent
Spanning Tree Prot.	802.1d-2004 RSTP	Transparent
Synchronization	SyncE	-
Carrier Ethernet	MEF9&14, HC, Packet Fragmentation	Transparent
Jumbo frames	Yes, 9600 bytes	Yes, 9600 bytes
Encryption	AES 256-bit**, licensed feature	-
Management	SNMP v1/2c/3, SSH, Telnet, HTTPS, Serial, RADIUS, Network Time Protocol	
	In-band MNG over same ETH port	Either Out-of-band or In-band MNG, depending on PN and firmware. In-band MNG supported only if PN has suffix "S1"
Perf. monitoring	Performance graphs, constellation diagram, alarms, detailed counters	
Electrical		
Power consumption	28...74 W depending on model and frequency band. See table below.	
Voltage range	Integra	36...57 V DC
	PoE Injector ¹	27...57 V DC in injector's "Vout = 57V" mode, 36...57 V DC in "Vout = Vin" mode.

* 5.8 GHz UL product is identical to L6 GHz in terms of specified parameters. For all bands, the maximum channel bandwidth of some radio modifications can be narrower than specified due to the limited tuning ranges. Inquire SAF representative for more information.

** Integra-G is FIPS 197 (Federal Information Processing Standards) validated and placed on validated product list, Validation No.: AES 5899: [SAF AES-256 Encryption Engine](#)

¹ Voltage range using I0ATPI43 Power over Ethernet Injector. The voltage drop in Ethernet cable must also be considered.

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia



Mechanical & environmental specification

Integra Model	Integra-G, Integra-W				
Antenna type	External antenna (default)	0.3m / 1ft, integrated	0.6m / 2ft, integrated		
Antenna interface	SAF2R 6...13 GHz SAF2 15...38 GHz	Integrated antenna, factory assembled with radio <i>(discontinued solution, no more available)</i>			
Stationary use	Conforms to ETSI EN 300 019 Class 4.1, NEMA 4X				
IP class	IP66: Integra-G 6...13 GHz models and Integra-W. IP67: Integra-G 15...38 GHz				
Relative Humidity	15 to 90-100% @ 30°C				
Temperature range	-33...+55 °C / -28...+130 °F				
Size, 15GHz and higher, w/o mount	235 x 250 x 72 mm / 9.26" x 9.85" x 2.84"	378 x 378 x 227 mm / 14.9" x 14.9" x 9"	669 x 669 x 289 mm / 26.3" x 26.3" x 11.4"		
Size, Integra -W 17/24 GHz UL	235 x 250 x 111 mm / 9.26" x 9.85" x 4.37"	N/A	N/A		
Size, 6...13 GHz	280 x 437 x 100 mm / 11.02" x 17.2" x 3.9"	N/A	N/A		
Weight, w/o mount	2.9 kg / 6.4 lbs	5 kg / 11 lbs	5 kg / 11 lbs		
Weight, Integra -W 17/24 GHz UL	4.9 kg / 10.8 lbs	N/A	N/A		
Weight, 6...13 GHz	6.5 kg / 14.3 lbs	N/A	N/A		
Mount	Mount size	Mount on antenna	292 x 176 x 250 mm / 11.5" x 7" x 10" max		
	Pole size		Ø 40 – 120 mm / Ø 1.6" – 4.7"		
	Weight		2.55 kg / 5.6 lbs		

* Inquire SAF representative for more information

Power consumption and rated current at 36 – 57 V DC²

Model	L6 GHz	U6, 7, 8 GHz	11, 13 GHz	15 GHz	17 GHz	18 GHz	23 GHz	24 GHz	25, 26, 28 GHz	38 GHz
Integra-G	Power [W] @ 36–57V DC	74	69	65	40	35	45 ³	41	38	45
	Current [A] @ 36 V DC	2.1	1.9	1.8	1.1	1.0	1.3	1.1	1.1	1.3
	Current [A] @ 48 V DC	1.5	1.4	1.4	0.8	0.7	1.0	0.9	0.8	0.9
	Current [A] @ 57 V DC	1.3	1.2	1.1	0.7	0.6	0.8	0.7	0.8	0.8
Integra-W	Power [W] @ 36–57V DC	70	64	51	31	28	35	35	30	36
	Current [A] @ 36 V DC	1.9	1.8	1.4	0.9	0.8	1.0	1.0	0.8	1.0
	Current [A] @ 48 V DC	1.5	1.3	1.1	0.6	0.6	0.7	0.7	0.6	0.8
	Current [A] @ 57 V DC	1.2	1.1	0.9	0.5	0.5	0.6	0.6	0.5	0.6

² Power consumption of Integra radio shown only. For power consumption of complete system add up to 8% (at 48V DC input) for PoE in DC/DC mode, around 4W for 100m cable (depends on cable) and approx. 1W for SFP transceiver, if used.

³ Both Standard and HP product versions



Exterior design of Integra-G and Integra-W models

		
5.8 GHz UL, 6 ...13 GHz models	Integra-W 17GHz and 24GHz UL	15GHz and higher

FCC & IC IDs for Integra UL versions

Integra-G 5.8 GHz: FCC ID: W9Z-INTEGRA5G8 IC ID: 8855A-INTEGRA5G8	Integra-G 24 GHz: FCC ID: W9Z-INTEGRA24 IC ID: 8855A-INTEGRA24	Integra-W 24 GHz: FCC ID: W9Z-INTEGRA24W IC ID: 8855A-INTEGRA24W
---	--	--

Maximum Tx Power [dBm] for Integra-G

1) For all ETSI channels, and FCC 60 MHz channel in fixed and variable Tx power modes:

"Fix" – Fixed Tx power mode for all channels mentioned above, and Variable Tx power mode for ETSI \leq 14 MHz channels.

"Var" – Variable Tx power mode for all ETSI channels, except 1.75, 3.5, 7 and 14 MHz, and for the FCC 60 MHz channel.

Modulation	L6, U6, 7, 8 GHz		11 GHz	15 GHz, 18 GHz HP ⁴	18, 23, 26, 28 GHz		17 GHz ⁵ , 24 GHz ⁵	38 GHz			
	Fix	Var	Fix	Var	Fix	Var	Fix	Var	Fixed	Variable \leq 14 MHz	Var
4 QAM	+31		+26		+23		+20		-22 ... +5	+15	+15
16 QAM	+30		+25		+22		+19		-22 ... +5	+14	+14
32 QAM	+29		+24		+21		+18		-22 ... +5	+14	+13
64 QAM	+28		+23		+20		+17		-22 ... +5	+13	+12
128 QAM	+28	+27	+23	+22	+20	+19	+17	+16	-22 ... +5	+13	+12
256 QAM	+27	+25	+22	+20	+19	+17	+16	+14	-22 ... +5	+12	+11
512 QAM	+26	+24	+21	+19	+18	+16	+15	+13	-22 ... +5	+11	+10
1024 QAM	+23		+18		+15		+12		-22 ... +5	+10	-
2048 QAM ⁶	+22		+17		+14		+11		-22 ... +5	+9	-

2) For FCC 5 to 50 MHz channels in fixed Tx power mode:

Frequency band	L6, U6, 7, 8 GHz	11 GHz			13 GHz			15 GHz, 18 GHz HP ⁴			18, 23, 25, 26, 28 GHz			17 GHz ⁵ , 24 GHz ⁵	38 GHz
BW, MHz Modulation	50 40 30	25 40 20	10 5	50 40 30	25 20 5	10 5	50 40 30	25 20 5	10 5	50 40 30	25 20 5	5 ... 60	5 ... 60		
4 QAM	+30	+29	+27	+25	+24	+22	+25	+24	+22	+22	+21	+19	+19	+18	+16
16 QAM	+30	+29	+27	+25	+24	+22	+25	+24	+22	+22	+21	+19	+19	+18	+16
32 QAM	+29	+29	+27	+24	+24	+22	+24	+24	+22	+21	+21	+19	+18	+18	+16
64 QAM	+28	+28	+27	+23	+23	+22	+23	+23	+22	+20	+20	+19	+17	+17	+16
128 QAM	+28	+28	+27	+23	+23	+22	+23	+23	+22	+20	+20	+19	+17	+17	+16
256 QAM	+27	+27	+27	+22	+22	+22	+22	+22	+22	+19	+19	+19	+16	+16	+16
512 QAM	+26	+26	-	+21	+21	-	+21	+21	-	+18	+18	-	+15	+15	-
1024 QAM	+23	+23	-	+18	+18	-	+18	+18	-	+15	+15	-	-22 ... +5	+10	
2048 QAM ⁶	+22	-	-	+17	-	-	+17	-	-	+14	-	-	+11	-	-

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia



3) For FCC 5 to 60 MHz channels in variable Tx power mode:

Frequency band	L6, U6, 7, 8 GHz				11 GHz				13 GHz				15 GHz, 18 GHz HP ⁴				18, 23, 25, 26, 28 GHz				38 GHz			
BW, MHz Modulation	50 60	25 40	10 20	5 30	50 60	25 40	10 20	5 30	50 60	25 40	10 20	5 30	50 60	25 40	10 20	5 30	50 60	25 40	10 20	5 30	50 60	25 40	10 20	5 30
4 QAM	+31	+30	+29	+27	+26	+25	+24	+22	+26	+25	+24	+22	+23	+22	+21	+19	+20	+19	+18	+16	+15	+14	+13	+11
16 QAM	+30	+30	+29	+27	+25	+25	+24	+22	+25	+25	+24	+22	+22	+22	+21	+19	+19	+19	+18	+16	+14	+14	+13	+11
32 QAM	+29	+29	+29	+27	+24	+24	+24	+22	+24	+24	+24	+22	+21	+21	+21	+19	+18	+18	+18	+16	+13	+13	+13	+11
64 QAM	+28	+28	+28	+27	+23	+23	+23	+22	+23	+23	+23	+22	+20	+20	+20	+19	+17	+17	+17	+16	+12	+12	+12	+11
128 QAM	+27	+27	+27	+27	+22	+22	+22	+22	+22	+22	+22	+22	+19	+19	+19	+19	+16	+16	+16	+16	+11	+11	+11	+11
256 QAM	+25	+25	+25	+27	+20	+20	+20	+22	+20	+20	+20	+22	+17	+17	+17	+19	+14	+14	+14	+16	+9	+9	+9	+11
512 QAM	+24	+24	+24	-	+19	+19	+19	-	+19	+19	+19	-	+16	+16	+16	-	+13	+13	+13	-	+8	+8	+8	-
1024 QAM	+23	+23	+23	-	+18	+18	+18	-	+18	+18	+18	-	+15	+15	+15	-	+12	+12	+12	-	+7	+7	+7	-
2048 QAM ⁶	+22	+22	-	-	+17	+17	-	-	+17	+17	-	-	+14	+14	-	-	+11	+11	-	-	+6	+6	-	-

³ Preliminary data

⁴ Integra-G 18 GHz HP version has 3dB higher Tx power than standard version

⁵ Max Tx power settings depend on EIRP allowed by national regulatory and antenna size.

⁶ 2048QAM modulation is available only for Integra-G. It is not supported by legacy models and 17 GHz radio.

Maximum Tx Power [dBm] for Integra-W

Modulation	Tx Power, dBm						
	L6 GHz	U6 GHz	11 GHz	15, 18, 23, 25, 26, 28 GHz	17 GHz ⁵ , 24 GHz ⁵	38 GHz	
4 QAM	+33	+31	+28	+22	-26 ... +5	+17	
8 QAM	+33	+31	+28	+22	-26 ... +5	+17	
16 QAM	+32	+30	+27	+21	-26 ... +5	+16	
32 QAM	+31	+29	+26	+21	-26 ... +5	+16	
64 QAM	+30	+28	+25	+20	-26 ... +5	+15	
128 QAM	+30	+28	+25	+20	-26 ... +5	+15	
256 QAM	+30	+28	+25	+19	-26 ... +5	+14	
512 QAM	+30	+28	+25	+19	-26 ... +5	+14	
1024 QAM	+28	+26	+23	+17	-26 ... +5	+12	

⁵ Max Tx power settings depend on EIRP allowed by national regulatory and antenna size.

Integra-G RSL Thresholds at BER 10⁻⁶ and Total Payload Capacity (Mbps) for ETSI channels^{6, 7, 8}

Band-width, MHz	Modulation	Guaranteed RSL Threshold, dBm													Capacity, Mbps -G modes	Capacity, Mbps Legacy modes
		6GHz	7GHz	8GHz	11GHz	13GHz	15GHz	17GHz	18GHz	23GHz	24GHz	26GHz	28GHz	38 GHz		
1.75 ⁸	4QAM StrongFEC	-100	-99	-100	-99	-99.5	-98.5	-97	-99	-99	-99.5	-98.5	-98	-95	1.9	
	16QAM StrongFEC	-93	-93.5	-93.5	-92	-93	-91.5	-90.5	-92.5	-92	-92.5	-92.5	-92	-89	3.9	
	32QAM StrongFEC	-89	-89.5	-89.5	-88	-89	-87	-86	-88.5	-87.5	-88.5	-87.5	-87	-85	4.9	
	64QAM StrongFEC	-86	-86.5	-86.5	-85.5	-86	-84.5	-83.5	-85.5	-84.5	-86	-85	-85	-82	6.6	
	128QAM StrongFEC	-84	-83.5	-83.5	-82	-83	-80.5	-79.5	-81.5	-80	-82.5	-81.5	-82	-79	7.9	
	128QAM WeakFEC	-82	-81	-79.5	-79	-81	-76.5	-78	-79.5	-80.5	-79.5	-79	-77	-77	8.6	
3.5	4QAM StrongFEC	-97	-96	-97	-96	-96.5	-95.5	-94	-96	-96	-96.5	-95.5	-95	-92	4	
	16QAM StrongFEC	-90	-90.5	-90.5	-89	-90	-88.5	-87.5	-89.5	-89	-89.5	-89.5	-89	-86	8	
	32QAM StrongFEC	-86	-86.5	-86.5	-85	-86	-84	-83	-85.5	-84.5	-85.5	-84.5	-84	-82	10	
	64QAM StrongFEC	-83.5	-83.5	-83.5	-82.5	-83	-81.5	-80.5	-82.5	-81.5	-83	-82	-82	-79	13	
	128QAM StrongFEC	-80	-80.5	-80.5	-79	-80	-77.5	-76.5	-78.5	-77	-79.5	-78.5	-79	-76	16	
	128QAM WeakFEC	-77.5	-78	-76.5	-76	-78	-73.5	-75	-76.5	-75	-77.5	-76.5	-76	-74	17	

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia



Band-width, MHz	Modulation	6GHz	7GHz	8GHz	11GHz	13GHz	15GHz	17GHz	18GHz	23GHz	24GHz	26GHz	28GHz	38 GHz	Capacity, Mbps
		Guaranteed RSL Threshold, dBm													-G modes
7	4QAM StrongFEC	-94	-94.5	-94	-93	-94	-93	-91	-94	-93	-93.5	-92.5	-93	-90.5	8
	16QAM StrongFEC	-87	-87.5	-88.5	-86.5	-88	-86	-84.5	-87.5	-86	-87	-86	-86	-84	16
	32QAM StrongFEC	-84	-84.5	-84.5	-83.5	-84	-82.5	-80.5	-83.5	-82	-83.5	-82.5	-83	-80	20
	64QAM StrongFEC	-80.5	-81.5	-81.5	-80.5	-81	-80	-78	-80.5	-80	-80.5	-79	-80	-77.5	27
	128QAM StrongFEC	-77	-78	-78.5	-76.5	-77	-76	-75	-77.5	-77	-77.5	-76	-76.5	-74	33
	256QAM StrongFEC	-74	-74.5	-75	-73.5	-74.5	-73	-71	-74.5	-72	-73.5	-72.5	-73	-71	39
	512QAM WeakFEC	-72	-73	-67.5	-71.5	-72	-70	-69	-72.5	-71	-71.5	-69	-71	-69	41
14	4QAM StrongFEC	-91	-91	-92	-90.5	-91	-90	-88	-91	-87.5	-91	-90	-90	-87	17
	16QAM StrongFEC	-85	-85	-85.5	-84	-85	-83.5	-81.5	-84.5	-82	-84	-83.5	-84	-81	33
	32QAM StrongFEC	-80	-81	-81.5	-80	-80.5	-79	-77	-80.5	-78	-80	-79	-79	-77	44
	64QAM StrongFEC	-78	-78.5	-78.5	-77	-78.5	-77	-75	-78.5	-76	-78	-77	-77	-74	56
	128QAM StrongFEC	-75	-75.5	-74.5	-74	-71	-74	-72	-75.5	-73	-74.5	-73.5	-74	-71	67
	256QAM StrongFEC	-71.5	-72	-72.5	-71	-67	-71	-68.5	-71.5	-69.5	-71	-70.5	-70.5	-69	79
	512QAM StrongFEC	-68.5	-68	-69.5	-67	-63	-67	-65	-68.5	-67	-67.5	-67.5	-67	-65	90
20	512QAM WeakFEC	-65.5	-66	-66.5	-64.5	-61	-64	-61.5	-65.5	-63	-65	-64	-64	-62	97
	4QAM StrongFEC	-89	-90	-91	-88.5	-88.5	-88.5	-87	-89.5	-86	-89	-89.5	-89	-86	25
	16QAM StrongFEC	-83	-84	-84.5	-83	-81	-82.5	-80	-83.5	-81	-83	-82.5	-82.5	-79.5	51
	32QAM StrongFEC	-80	-80	-80.5	-79	-78	-78	-76.5	-79.5	-77	-79	-78.5	-79	-75.5	64
	64QAM StrongFEC	-77	-77	-77.5	-76.5	-74.5	-76	-74	-77	-75	-77	-75.5	-76	-73	85
	128QAM StrongFEC	-74	-74	-74.5	-73	-71.5	-73	-70.5	-74	-72	-73	-72.5	-73	-70	102
	256QAM StrongFEC	-70.5	-71	-71.5	-69.5	-67.5	-69.5	-68	-70.5	-68.5	-70	-70.5	-71	-67	119
28	512QAM StrongFEC	-67.5	-68	-67.5	-67	-65	-66	-64.5	-67.5	-65.5	-67	-66	-66	-63.5	136
	1024QAM StrongFEC	-64	-64	-64.5	-62.5	-61	-63	-60.5	-64.5	-62	-63	-62.5	-62	-60	153
	1024QAM WeakFEC	-62	-62	-60.5	-61	-58	-60	-58	-62.5	-59.5	-61	-60.5	-60	-58	163
	4QAM StrongFEC	-88	-89	-89	-88	-87	-87	-85	-88	-84	-88	-86.5	-87	-85	34
	16QAM StrongFEC	-82	-83	-83	-81.5	-79.5	-81	-79	-82.5	-79.5	-82	-81.5	-81	-78	69
	32QAM StrongFEC	-79	-79	-80	-77.5	-77	-77	-75	-78.5	-75.5	-78	-77.5	-77	-74	87
	64QAM StrongFEC	-76	-76	-76.5	-75.5	-74	-75	-72	-75.5	-73.5	-75	-74.5	-74.5	-72	114
40	128QAM StrongFEC	-73	-73	-73.5	-71.5	-70.5	-72	-69	-72.5	-70.5	-72	-71.5	-71	-69	137
	256QAM StrongFEC	-70	-70	-70	-68.5	-66.5	-68	-66	-69.5	-67.5	-69	-68	-68	-65	160
	512QAM StrongFEC	-66.5	-66	-67	-65	-63.5	-65	-62.5	-66.5	-64	-65	-64.5	-64	-62	183
	1024QAM StrongFEC	-63	-63	-62.5	-62	-59.5	-61.5	-59	-63.5	-61	-62	-61.5	-61	-58	206
	1024QAM WeakFEC	-61				-59.5		-59	-60.5	-59.5	-60	-58.5	-59	-56	220
	2048QAM StrongFEC	-59	-60	-60.5	-58	-56	-58	-59	-57	-59	-57	-58	-57	-54	226
	4QAM StrongFEC	-86.5	-87	-87	-85	-86	-85.5	-83	-86.5	-83	-85.5	-85	-85.5	-83	50
56	16QAM StrongFEC	-81	-81	-82	-79.5	-78.5	-79.5	-77	-81	-78.5	-80	-79.5	-79	-76.5	98
	32QAM StrongFEC	-77	-77	-78	-76.5	-75.5	-75.5	-73	-77	-74.5	-76	-75.5	-75.5	-73	125
	64QAM StrongFEC	-74	-74	-75	-73.5	-71	-73	-71	-74	-72	-73	-73.5	-73.5	-70.5	165
	128QAM StrongFEC	-71	-71	-72	-70.5	-70	-70.5	-67	-71	-69	-70	-69.5	-70	-67	198
	256QAM StrongFEC	-68	-68	-68	-67	-65	-66.5	-64	-68	-66	-67	-66.5	-66	-63.5	231
	512QAM StrongFEC	-65	-65	-65.5	-64	-62	-63.5	-61	-65	-63	-63.5	-63.5	-63	-60.5	264
	1024QAM StrongFEC	-61	-61	-61.5	-60.5	-59	-60	-57	-61.5	-59.5	-60.5	-59.5	-59	-56.5	298
6	1024QAM WeakFEC	-59			-59	-57	-55	-59	-57.5	-58.5	-58	-57.5	-57.5	-55	314
	2048QAM StrongFEC	-58	-58	-58.5	-56.5	-54	-56	-57.5	-55.5	-56.5	-56	-56	-56	-52.5	327
	4QAM StrongFEC	-85	-85	-86	-84	-84.5	-84	-81	-85	-82	-84	-83.5	-84	-81	72
	16QAM StrongFEC	-79	-79.5	-80	-78.5	-78	-78	-75	-79	-77	-78.5	-78	-78	-75	145
	32QAM StrongFEC	-75	-75.5	-76	-74.5	-74	-74	-71.5	-75	-73	-74.5	-73.5	-74	-72	183
	64QAM StrongFEC	-72	-73	-74	-72	-71	-71	-69	-72	-70	-72.5	-71	-71	-69	238
	128QAM StrongFEC	-70	-69.5	-70	-68.5	-68	-69	-66	-69	-67.5	-69.5	-68	-68	-65	286
56	256QAM StrongFEC	-67	-66	-67	-65.5	-64	-65	-62	-66	-64.5	-65.5	-64.5	-65	-62	334
	512QAM StrongFEC	-63	-63.5	-64	-62	-61	-62	-59	-63	-61.5	-62.5	-61	-62	-59	382
	1024QAM StrongFEC	-60	-60	-60	-58.5	-58	-58	-56	-59	-57.5	-59.5	-57.5	-58	-55	430
	1024QAM WeakFEC	-58			-57	-55	-54	-57.5	-55.5	-55.5	-55.5	-55.5	-54	-54	456
	2048QAM StrongFEC	-56	-57	-57	-54.5	--55	-54	-55	-53.5	-55.5	-54	-54.5	-52	-472	

⁶ 2048QAM modulation is available only for Integra-G. It is not supported by legacy models and 17 GHz radio.

⁷ 1024QAM modulation with Weak FEC setting is available for legacy models or in legacy modes only.

⁸ 1.75 MHz bandwidth is available on all Integra-G models but is being tested on customized products only. RSL values are preliminary for all bands except 6 and 13 GHz. Please ask SAF representative for more information.



Integra-G RSL Thresholds at BER 10⁻⁶ and Total Payload Capacity (Mbps) for FCC channels^{6,7}

BW, MHz	Modulation	6GHz	7GHz	8GHz	11GHz	13GHz	15GHz	17GHz	18GHz	23GHz	24GHz	26GHz	28GHz	38 GHz	Capacity, Mbps	
		Guaranteed RSL Threshold, dBm													-G modes	Legacy modes
5	4QAM StrongFEC	-96	-96	-96.5	-95	-95.5	-94	-92.5	-95	-94	-95.5	-94.5	-95	-91	5	
	16QAM StrongFEC	-89	-89.5	-86.5	-88	-89	-87	-86.5	-88.5	-88	-89	-87.5	-88	-85	10	
	32QAM StrongFEC	-85	-85.5	-85.5	-84	-85	-83.5	-82.5	-84.5	-84	-85	-83.5	-84	-81	12	
	64QAM StrongFEC	-82.5	-82.5	-80.5	-81.5	-82	-80.5	-79.5	-81.5	-81	-82	-81	-81	-79	17	
	128QAM StrongFEC	-79	-79.5	-79.5	-78.5	-79	-77.5	-76.5	-78.5	-77.5	-79	-78	-78	-75	20	
	128QAM WeakFEC	-77	-77	-77	-76.5	-77	-74	-73.5	-76.5	-75.5	-76.5	-75.5	-75.5	-73	22	
10	4QAM StrongFEC	-92	-92.5	-94	-91	-92.5	-91	-89	-92	-90	-92	-91.5	-91.5	-89	12	
	16QAM StrongFEC	-86	-86.5	-86.5	-85	-86	-84.5	-82.5	-85.5	-84	-85.5	-84.5	-85	-82	24	
	32QAM StrongFEC	-82	-82.5	-82.5	-81.5	-82	-81	-79	-82.5	-80	-82	-81	-81	-78	30	
	64QAM StrongFEC	-79.5	-80	-80	-79	-79.5	-78	-76	-79.5	-78	-79	-78	-78	-76	40	
	128QAM StrongFEC	-76	-76.5	-76.5	-75.5	-76	-75	-73	-76.5	-75	-76	-75	-75	-73	48	
	256QAM StrongFEC	-73	-73.5	-73.5	-72	-73	-72	-69	-72.5	-71	-72.5	-71.5	-71	-70	56	
20	256QAM WeakFEC	-70	-70.5	-70.5	-69	-70	-69	-66.5	-70.5	-68	-69.5	-68.5	-68.5	-66	60	
	4QAM StrongFEC	-89	-90	-91	-88.5	-88.5	-88.5	-86	-89	-86.5	-89	-88.5	-88	-86	24	
	16QAM StrongFEC	-83	-84	-84.5	-83	-81	-83	-80	-83.5	-81	-83	-82.5	-82.5	-80	49	
	32QAM StrongFEC	-80	-80	-80.5	-79	-78	-79	-76.5	-79.5	-77	-79	-78.5	-79	-77	62	
	64QAM StrongFEC	-77	-77	-77.5	-76.5	-74.5	-76	-74	-76.5	-74.5	-77	-75.5	-76	-73	82	
	128QAM StrongFEC	-74	-74	-74.5	-73	-71.5	-73	-70.5	-73.5	-71.5	-73	-72.5	-73	-71	99	
25	256QAM StrongFEC	-70.5	-71	-71.5	-69.5	-67.5	-70	-67	-70.5	-68.5	-70	-69.5	-70	-67.5	115	
	512QAM StrongFEC	-67.5	-68	-67.5	-67	-65	-66	-64.5	-67.5	-65.5	-67	-66	-66	-64	132	
	1024QAM StrongFEC	-64	-64	-64.5	-62.5	-61	-63	-60.5	-64.5	-62.5	-63	-62.5	-62	-61	148	
	1024QAM WeakFEC	-62	-62	-60.5	-61	-58	-60	-58	-62.5	-59.5	-61	-60.5	-60	-58	157	
	4QAM StrongFEC	-88	-88.5	-89.5	-88	-88	-88	-85	-88	-85	-88	-87.5	-87	-85	31	
	16QAM StrongFEC	-82	-83	-83.5	-82.5	-81	-82	-79	-82.5	-80	-82	-81.5	-81.5	-79	62	
30	32QAM StrongFEC	-79	-79	-79.5	-78.5	-76.5	-78	-75.5	-78.5	-77	-78.5	-77.5	-78	-75	78	
	64QAM StrongFEC	-76	-76	-76.5	-75.5	-74	-75	-73	-76.5	-73.5	-75.5	-74.5	-75	-72	104	
	128QAM StrongFEC	-73	-73	-73.5	-72.5	-70.5	-72	-70	-72.5	-70.5	-72.5	-71.5	-72	-69	124	
	256QAM StrongFEC	-70	-70	-69.5	-69.5	-65.5	-69	-66	-69.5	-68	-69	-68.5	-68	-66	145	
	512QAM StrongFEC	-66.5	-67	-66.5	-65.5	-63	-66	-63	-66.5	-65	-66	-65.5	-64.5	-63	166	
	1024QAM StrongFEC	-63	-63	-63.5	-61.5	-59	-62	-59	-63.5	-61.5	-62.5	-61.5	-61	-60	187	
40	1024QAM WeakFEC	-61	-61	-61.5	-59.5	-58	-58	-57	-60.5	-59.5	-60	-59.5	-59	-57	198	
	4QAM StrongFEC	-88	-88	-89	-87	-87	-87	-85	-88	-84.5	-87	-86.5	-86.5	-84	37	
	16QAM StrongFEC	-82	-82	-83	-81.5	-79.5	-81	-78.5	-81.5	-79	-81.5	-80.5	-81	-78	73	
	32QAM StrongFEC	-78	-79	-79	-77.5	-76.5	-77	-75	-78.5	-75	-77.5	-76.5	-77	-74	93	
	64QAM StrongFEC	-76	-76	-76.5	-74.5	-74	-74	-72	-75.5	-73	-75	-74.5	-74	-71.5	123	
	128QAM StrongFEC	-72	-73	-73	-71.5	-70	-71	-69	-72.5	-70	-71.5	-71.5	-71	-69	148	
50	256QAM StrongFEC	-69	-69	-69.5	-68.5	-67	-68	-66	-69	-67.5	-68.5	-67.5	-68	-65	173	
	512QAM StrongFEC	-66	-66	-66.5	-65.5	-62.5	-65	-62	-66.5	-64.5	-65	-64.5	-64	-62	197	
	1024QAM StrongFEC	-63	-62	-62.5	-61.5	-60	-61	-59	-62.5	-61.5	-61.5	-61	-60	-58	222	
	1024QAM WeakFEC	-61			-60		-58	-57	-60.5	-59.5	-60.5	-59	-58.5	-56	235	
	2048QAM StrongFEC	-59	-60	-60.5	-58	-56.5	-56	-58	-57	-58.5	-57	-57.5	-54	244		
	4QAM StrongFEC	-86.5	-87	-87	-85	-86	-85.5	-83	-86	-85.5	-85	-85.5	-82	51		
60	16QAM StrongFEC	-81	-81	-82	-81.5	-79.5	-81	-78.5	-81.5	-79	-81.5	-80.5	-81	-78	73	
	32QAM StrongFEC	-77	-77	-78	-76.5	-75.5	-76	-73	-77	-74	-76	-75.5	-75	-73	129	
	64QAM StrongFEC	-74	-74	-75	-73.5	-71	-73	-70	-74	-72	-73	-72.5	-72.5	-70	170	
	128QAM StrongFEC	-71	-71	-72	-70.5	-70	-70	-67	-71	-69	-70	-69.5	-70	-67	204	
	256QAM StrongFEC	-68	-68	-68	-67	-65	-66.5	-64.5	-67	-66	-67	-66.5	-65.5	-64	238	
	512QAM StrongFEC	-65	-65	-65.5	-64	-62	-64	-61	-64.5	-63	-63.5	-63.5	-63	-61	272	
70	1024QAM StrongFEC	-61	-61	-61.5	-60.5	-59	-58	-57.5	-61.5	-59	-60.5	-59.5	-59.5	-56.5	306	
	1024QAM WeakFEC	-60			-59		-55	-55	-59.5	-57.5	-58.5	-58	-57.5	-55.5	323	
	2048QAM StrongFEC	-58	-58	-58.5	-57	-54	-53	-57.5	-55	-56.5	-55.5	-56	-53	336		
	4QAM StrongFEC	-85	-86	-84.5	-85.5	-85	-82	-85	-82.5	-85.5	-84	-84	-81.5	63	63	
	16QAM StrongFEC	-80	-80	-80	-78.5	-78	-78	-76	-79.5	-77	-78	-78	-76	128	130	
	32QAM StrongFEC	-76	-76	-76	-74.5	-74.5	-75	-72	-75.5	-73	-75.5	-74.5	-74.5	-72.5	163	163
80	64QAM StrongFEC	-73	-73.5	-74	-72.5	-71	-72	-69	-72	-71	-72.5	-71.5	-72	-69.5	212	216
	128QAM StrongFEC	-70	-70	-71	-69	-68	-69	-66	-70	-68	-69.5	-68	-69	-66.5	254	258
	256QAM StrongFEC	-67	-67	-67	-65.5	-64	-66	-63	-66	-64.5	-66.5	-65	-65	-63	297	301
	512QAM StrongFEC	-64	-63.5	-64	-63	-61	-63	-59	-63.5	-62	-63	-62	-62	-60	339	344
	1024QAM StrongFEC	-61	-61	-60	-60	-57	-58	-56	-60	-58.5	-59.5	-58.5	-58	-56	382	385
	1024QAM WeakFEC	-59			-57		-55	-54	-57.5	-55.5	-57.5	-56	-56	-54	410	
90	2048QAM StrongFEC	-57	-57	-57.5	-56	-55	-53	-	-56	-56.5	-55.5	-55	-52	420		

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia



BW, MHz	Modulation	6GHz	7GHz	8GHz	11GHz	13GHz	15GHz	17GHz	18GHz	23GHz	24GHz	26GHz	28GHz	38 GHz	Capacity, Mbps	
		Guaranteed RSL Threshold, dBm													-G modes	Legacy modes
60	4QAM StrongFEC	-84	-85	-85.5	-83.5	-84.5	-84	-81	-85	-82	-84	-83.5	-83.5	-81	74	74
	16QAM StrongFEC	-79	-79.5	-80	-78	-77	-78	-75	-78.5	-76	-78.5	-77	-77.5	-75	149	151
	32QAM StrongFEC	-75	-75.5	-76	-74.5	-73	-74	-71	-75	-73	-74.5	-73.5	-74	-71	190	190
	64QAM StrongFEC	-72	-73	-73	-71.5	-71	-71	-69	-72	-70	-71.5	-71	-71	-69	247	251
	128QAM StrongFEC	-70	-69.5	-70	-68.5	-68	-68	-66	-69	-67	-69	-67.5	-68	-65	297	301
	256QAM StrongFEC	-66	-66	-67	-65	-64	-65	-62	-66	-64.5	-65.5	-64.5	-65	-62	347	351
	512QAM StrongFEC	-63	-63	-63	-62.5	-61	-62	-59	-62.5	-61.5	-62.5	-61	-61	-59	397	401
	1024QAM StrongFEC	-60	-59	-60	-58.5	-58	-58	-55	-59	-57.5	-58.5	-57.5	-57	-54.5	447	451
	1024QAM WeakFEC	-58			-57		-55	-53	-57	-55.5	-56.5	-55.5	-55.5	-53		474
	2048QAM StrongFEC	-56	-56	-57	-54	-54	-54	-55	-53	-55.5	-54.5	-54	-51.5		491	

⁶ 2048QAM modulation is available only for Integra-G. It is not supported by legacy models and 17 GHz radio

⁷ 1024QAM modulation with Weak FEC setting is available for legacy models or in legacy modes only

Integra-W RSL Thresholds at BER 10⁻⁶ and Total Payload Capacity (Mbps) ⁹

		6L GHz	6U GHz	11GHz	15GHz	17GHz ¹⁰	18GHz	23GHz	24GHz ¹⁰	26GHz	28GHz	38 GHz	Capacity, Mbps	
BW, MHz	Modulation, Strong FEC	Guaranteed RSL Threshold, dBm												Integra -W
40	4QAM	-82.5	-82.5	-82.5	-82	-79	-83.5	-80.5	-80	-82	-82.5	-79		63
	8QAM	-79	-79	-78	-77.5	-76	-80.5	-76.5	-75.5	-78	-78.5	-75		94
	16QAM	-76	-76	-75.5	-75	-73	-76.5	-74.5	-72.5	-75	-74.5	-72.5		126
	32QAM	-73	-73	-73	-72.5	-70	-74	-71.5	-70	-72	-72	-69.5		157
	64QAM	-70	-70	-70	-69.5	-67.5	-71.5	-69.5	-66.5	-69	-66.5	-66.5		189
	128QAM	-67	-67	-67	-66.5	-64.5	-68	-65.5	-64	-66	-66.5	-63.5		220
	256QAM	-64	-64	-64	-63.5	-61	-63.5	-62.5	-60.5	-63	-61.5	-60.5		252
	512QAM	-61	-61	-60	-59.5	-58	-59.5	-59.5	-57.5	-60	-59.5	-57.5		284
	1024QAM	-57	-57	-56.5	-56	-55	-55.5	-57	-54	-56	-55.5	-53		315
	4QAM	-82	-82	-82	-81.5	-79	-82.5	-79.5	-79	-81	-81	-78.5		78
50	8QAM	-78	-78	-77	-76.5	-75	-79	-75.5	-75	-77	-77	-74.5		118
	16QAM	-75	-75	-75	-74.5	-72	-76.5	-74.5	-72	-74	-74	-72		157
	32QAM	-72	-72	-72	-71.5	-69.5	-73.5	-71.5	-69	-71	-71	-69		197
	64QAM	-69	-69	-69	-68.5	-66.5	-70.5	-68.5	-66	-68	-68.5	-66		236
	128QAM	-66	-66	-66	-65.5	-63.5	-65.5	-65.5	-62.5	-65.5	-66.5	-64		276
	256QAM	-63	-63	-63	-62.5	-60	-62.5	-61.5	-60	-62	-62	-60		315
	512QAM	-60	-60	-60	-59.5	-57.5	-58.5	-58.5	-57	-59	-59	-57		355
	1024QAM	-56	-56	-56	-55.5	-54	-55.5	-55.5	-53	-55	-54.5	-52.5		394
	4QAM	-81.5	-81.5	-81	-80.5	-78.5	-82.5	-80.5	-78	-80	-80.5	-77.5		89
	8QAM	-77	-77	-76	-75.5	-74.5	-78	-75.5	-73	-76	-76.5	-73.5		134
56	16QAM	-74.5	-74.5	-74	-73.5	-72	-75.5	-74	-71	-74	-74	-71		178
	32QAM	-71.5	-71.5	-71	-70.5	-69	-72.5	-70.5	-68.5	-71	-71.5	-69.5		224
	64QAM	-68.5	-68.5	-68.5	-68	-66	-68.5	-67.5	-65	-68	-68	-66		269
	128QAM	-65	-65	-65	-64.5	-63	-65.5	-65	-62	-65	-65	-62		314
	256QAM	-62.5	-62.5	-62.5	-62	-60	-61.5	-61.5	-59	-62	-62.5	-59.5		359
	512QAM	-59.5	-59.5	-59	-58.5	-57	-58.5	-58.5	-56	-58	-59	-56		404
	1024QAM	-55	-55	-55.5	-55	-53	-54.5	-55	-52.5	-55	-55.5	-52.5		449
	4QAM	-81	-81	-81	-80.5	-78.5	-81.5	-80.5	-78	-80	-80	-77.5		96
	8QAM	-76.5	-76.5	-76	-75.5	-74	-78	-75.5	-74	-76	-76	-73.5		144
	16QAM	-74.5	-74.5	-74	-73.5	-71.5	-75.5	-73.5	-71	-74	-74.5	-72		192
60	32QAM	-71.5	-71.5	-71	-70.5	-68.5	-72.5	-70.5	-68	-71	-71.5	-68.5		240
	64QAM	-68.5	-68.5	-67.5	-67	-64.5	-67.5	-67.5	-65	-67	-67	-65		288
	128QAM	-65	-65	-65	-64.5	-62.5	-65.5	-64.5	-62	-65	-65.5	-62.5		336
	256QAM	-62.5	-62.5	-62	-61.5	-59.5	-61.5	-61.5	-59	-61	-61.5	-58.5		385
	512QAM	-59	-59	-58	-57.5	-56.5	-58.5	-58.5	-55.5	-58	-58	-56		433
	1024QAM	-55	-55	-55	-54.5	-53	-54.5	-55	-52	-55	-54.5	-52		481
	4QAM	-79.5	-79.5	-79.5	-79	-77.5	-81	-78.5	-76	-79	-79	-76.5		128
	8QAM	-75.5	-75.5	-74	-73.5	-72.5	-77	-75	-73	-75	-75	-72.5		192
	16QAM	-72.5	-72.5	-72	-71.5	-70	-74.5	-71.5	-70	-72	-72	-69.5		257
	32QAM	-69.5	-69.5	-69	-68.5	-67.5	-71.5	-68.5	-67	-69	-69	-66.5		321
80	64QAM	-66.5	-66.5	-66.5	-66	-64.5	-67.5	-65.5	-64	-66	-66	-63.5		385
	128QAM	-63.5	-63.5	-63.5	-63	-61	-64	-62.5	-61	-63	-63	-60.5		450
	256QAM	-60.5	-60.5	-60.5	-60	-58	-60.5	-59.5	-58	-60	-60	-57.5		514
	512QAM	-57.5	-57.5	-57	-56.5	-55	-57	-56.5	-54	-56.5	-56.5	-54		578
	1024QAM	-53.5	-53.5	-53.5	-53	-51.5	-53.5	-53	-51	-53.5	-53.5	-51		643

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia



		6L GHz	6U GHz	11GHz	15GHz	17GHz ¹⁰	18GHz	23GHz	24GHz ¹⁰	26GHz	28GHz	38 GHz	Capacity, Mbps	
BW, MHz	Modulation, Strong FEC	Guaranteed RSL Threshold, dBm												Integra -W
100 ⁹	4QAM	-78.5	-78.5	-79	-78.5	-	-80	-77.5	-	-78.5	-78.5	-76	168	
	8QAM	-74.5	-74.5	-74	-73.5	-	-76	-73.5	-	-73.5	-73.5	-71	252	
	16QAM	-71.5	-71.5	-71	-70.5	-	-73	-70.5	-	-71.5	-71.5	-69	336	
	32QAM	-68.5	-68.5	-69	-68.5	-	-70	-67.5	-	-68.5	-68.5	-66	420	
	64QAM	-65.5	-65.5	-65.5	-65	-	-66	-64.5	-	-65.5	-65.5	-63	504	
	FCC	128QAM	-63	-63	-63	-62.5	-	-63	-61.5	-	-62.5	-62.5	-60	588
		256QAM	-59.5	-59.5	-59.5	-59	-	-60	-58.5	-	-58.5	-58.5	-56	672
		512QAM	-56	-56	-56	-55.5	-	-56	-55.5	-	-56.5	-56.5	-54	756
112 ⁹		1024QAM	-52	-52	-51	-50.5	-	-51.5	-52	-	-51.5	-51.5	-49	840
		4QAM	-78.5	-78.5	-77.5	-77	-	-79.5	-77.5	-	-77.5	-77.5	-75	176
		8QAM	-73.5	-73.5	-73.5	-73	-	-76	-73	-	-73	-73	-70.5	265
		16QAM	-71.5	-71.5	-71	-70.5	-	-73	-70.5	-	-70.5	-70.5	-68	353
		32QAM	-68.5	-68.5	-68	-67.5	-	-70	-67.5	-	-67.5	-67.5	-65	441
		64QAM	-65	-65	-65	-64.5	-	-66	-64.5	-	-64.5	-64.5	-62	530
	ETSI	128QAM	-62.5	-62.5	-62	-61.5	-	-63	-61.5	-	-61.5	-61.5	-59	618
		256QAM	-59.5	-59.5	-59	-58.5	-	-59	-58.5	-	-58.5	-58.5	-56	707
512QAM		512QAM	-54.5	-54.5	-56	-55.5	-	-56	-54.5	-	-54.5	-54.5	-52	795
		1024QAM	-52	-52	-51.5	-51	-	-51.5	-51	-	-51.5	-51.5	-49	883

⁹ 100 MHz and 112 MHz channel bandwidths are available for all Integra-W models except 17GHz and 24GHz UL.

¹⁰ Please check the availability of 17GHz and 24GHz UL Integra-W models at SAF representative before planning your network

SAF Tehnika JSC contacts: Telephone: +371 67046840; Fax: +371 67046809
e-mail: info@saftehnika.com; www.saftehnika.com
24a Ganibu Dambis, Riga LV-1005, Latvia

