



# Chateau LTE7

Your best friend when it comes to mobile networks.



EXPANDED FREQUENCY SUPPORT (B28 & B32)



STRONG DUAL-BAND, DUAL-CHAIN RADIO



LTE CONNECTIONS UP TO 300 MBPS



POWERFUL QUAD-CORE ARM CPU



FAST AND RESPONSIVE LTE CATEGORY 7 MODEM



5X GIGABIT ETHERNET PORTS

Chateau LTE7 keeps the same elegant design, powerful hardware, and flexible RouterOS features that made the Chateau series a global favorite – now upgraded with a faster LTE Category 7 modem, expanded frequency support, and a lower price than the previous LTE6 model.



## One router for home, office, and everything in-between

Chateau LTE7 was designed to replace the weak, feature-limited contact routers often supplied by service providers.

It features a purposeful balance of performance, flexibility, and clean design that fits naturally into modern homes and offices – without looking like a piece of industrial equipment.

- 5× Gigabit Ethernet ports for wired devices, NAS, TVs, or PCs
- Use LTE as:
  - your main internet connection
  - or a reliable backup to wired ISP services
- Dual-band, dual-chain Wi-Fi for reliable everyday wireless coverage even in large homes or offices

Whether LTE is your primary connection or a fallback link – Chateau adapts to your setup.

## Powerful when you need it. Simple when you don't.

At the heart of Chateau LTE7 is a powerful quad-core ARM CPU, paired with full RouterOS v7 functionality.

- That means you can:
- Run secure VPNs for remote work
  - Configure advanced firewall rules
  - Set up VLANs and traffic prioritization
  - Monitor usage and automate notifications
  - Use containers for custom services

Or... you can simply plug it in and forget it exists. Chateau is built to scale with your knowledge and lifestyle – equally useful to network professionals, researchers, homelab enthusiasts, as well as regular households with limited IT skills.



## Powered by RouterOS v7 – automate, adapt, and configure anything to your liking!

Firewalling, VPNs, VLANs, DHCP, routing policies, advanced notifications, GPS data processing, custom scripts – RouterOS v7 gives you full control. No paywalls, no subscriptions, only pure functionality... forever! We have been making our own software since 1996. With each new version our priority remained the same: to provide users with the freedom to explore different setups and always have the right tools for the job.

## Remove the bottleneck in your LTE setup

Chateau supports 2x2 MIMO DL and carrier aggregation. That means it can use multiple LTE bands simultaneously. That's a huge advantage when there are a lot of mobile users in the area. It offers **better responsiveness** in a crowded environment. And **higher efficiency for weaker signal situations** in the countryside. Win-win! We have seen Internet speed doubling in rural areas after enabling carrier aggregation.

## Why Upgrade to CAT7

- ✓ Twice the upload speed\*
- ✓ Expanded frequency support – now includes Band 32 (1500 MHz) for even better performance in congested areas.
- ✓ Same trusted design – no changes to installation or configuration.
- ✓ Lower cost – better connectivity that actually costs less, especially on volume orders.

*\* Depending on the LTE tower infrastructure and other variables.*

***You don't have to wait for cable network expansion to have fast and steady Internet at home. Mobile networks are great. If you're using a Chateau.***

## • Specifications

Product code	D53G-5HacD2HnD-TC&R11e-LTE7
CPU	Quad-Core IPQ-4019 448-896 MHz (auto)
CPU architecture	ARM 32bit
Size of RAM	256 MB
RAM type	DDR3L
Storage	16 MB Flash
Number of 1G Ethernet ports	5
USB port	1 (2.0 type A)
Switch chip model	IPQ-4019
Wireless interface model	IPQ-4019 (2.4 GHz), IPQ-4019 (5 GHz)
Wireless	2.4 GHz 802.11b/g/n dual-chain, 5 GHz 802.11a/n/ac dual-chain
Antenna gain	2.4 GHz - 2 dBi, 5 GHz - 4 dBi
LTE category	7 (DL: 300 Mbps; UL: 100 Mbps)
LTE modem	R11e-LTE7
TAC	35312597
MIMO DL	2x2
MIMO UL	1x1
LTE FDD bands	1 (2100 MHz) / 3 (1800 MHz) / 5 (850 MHz) / 7 (2600 MHz) / 8 (900 MHz) / 20 (800 MHz) / 28 (700 MHz)
LTE TDD bands	38 (2600 MHz) / 40 (2300 MHz) / 41 (2500 MHz)
3G Category	R8 (DL: 42.2 Mbps; UL: 5.76 Mbps)
3G bands	1 (2100 MHz) / 3 (1800 MHz) / 5 (850 MHz) / 8 (900 MHz)
Dimensions	240 x 156 x 44 mm
Operating system	RouterOS v7, License level 4
Operating temperature	-40°C to +70°C

## • Powering

Number of DC inputs	1
DC jack input Voltage	12-28 V
Power adapter nominal voltage	24 V
Power adapter nominal current	1.2 A
Max power consumption without attachments	16 W
Max power consumption	21 W

## • Wireless specifications

Rate (2.4 GHz)	Tx (dBm)	Rx (dBm)	Rate (5 GHz)	Tx (dBm)	Rx (dBm)
1MBit/s	25	-100	6MBit/s	26	-96
11MBit/s	25	-94	54MBit/s	22	-80
6MBit/s	26	-95	MCS0	26	-96
54MBit/s	23	-78	MCS7	21	-75
MCS0	26	-96	MCS9	19	-70
MCS7	22	-73			

## • Supported 2xCA combinations

B1+B1/3/5/7/8/20/28/32/40/41 (100MHz)	B20+B1/3/7/32/38/40
B3+B1/3/5/7/8/20/28/32/40/41 (100MHz)	B28+B1/3/5/7/32
B5+B1/3/5/7/28/40/41 (100MHz)	B38+B38
B7+B1/3/5/8/20/28	B40+B40
B8+B1/3/7/20/32/40/41 (100MHz)	B41+B41 (100MHz)


## • Supported 2xCA (UL) LTE bands (Intra-band contiguous only)

B1+B1	B8+B8
B3+B3	B38+B38
B5+B5	B40+B40
B7+B7	B41+B41

## • Included parts



24 V 1.2 A  
power adapter



UTP Flat  
Cable (1.5m)